








350mA LED DRIVERS

Constant Current Drivers

LEDs use specific drivers to run them, they are different from normal low voltage fittings in that they must be wired in series and need a constant current. Drivers can be placed 10m from the LEDs. Longer distances of 10-40m can be achieved by using a larger diameter cable to reduce the volt drop, or taking one LED off the maximum the driver can run. Please contact us for more information.

Example fittings that use these drivers include: LD41-350, LD42-350, LD150-350, LD10236-350, LD26-350, LD36-350

| 350mA Constant Current Drivers | Replaces TXDP12 | | | | Replaces TXDD350 | | | Replaces TXDL20 TXDD350D | | | | |
|---|-----------------|--------------|---|---------------|------------------|---------------|---------------|-----------------------------|---------------|-------------------------------|----------------------|---------------------------------|
| | TXDELT350S | TX.DALV350S | TXDTC350S | TXDTC350D | TXDTC350DALI | TXDEL350S | TXDEL350CAS | TXDEL350D | TXDEL350DALI | TXDEL4S350D | TXDEL4A350DALI-1 | TXDEL4A350DMX TXDEL4A350DALI |
| Brand | ELT | Alvit | TCI | TCI | TCI | eldoLED | eldoLED | eldoLED | eldoLED | eldoLED | eldoLED | eldoLED |
| 1.2W fittings  | 3-9 | 1-12 | 1-13 | 1-13 | 4-15 | 1-17 | 1-17 | 1-17 | 1-17 | 72 (4 x 1-18) | 72 (4 x 1-18) | 72 (4 x 1-18) |
| 3.6W (3x1.2W) fittings  | 1-2 | 1-3 | 1-3 | 1-3 | 1-3 | 1-4 | 1-4 | 1-4 | 1-4 | 16 (4 x 1-4) | 16 (4 x 1-4) | 16 (4 x 1-4) |
| 5W fittings  | 1-2 | 1-3 | 1-3 | 1-3 | 1-3 | 1-4 | 1-4 | 1-4 | 1-4 | 16 (4 x 1-4) | 16 (4 x 1-4) | 16 (4 x 1-4) |
| 3.5W fittings  | 1-2 | 1-4 | 1-4 | 1-4 | 1-4 | 1-5 | 1-5 | 1-5 | 1-5 | 20 (4 x 1-5) | 20 (4 x 1-5) | 20 (4 x 1-5) |
| 7W fittings  | 1 | 1-2 | 1-2 | 1-2 | 1-2 | 1-2 | 1-2 | 1-2 | 1-2 | 8 (4 x 1-2) | 8 (4 x 1-2) | 8 (4 x 1-2) |
| 14W fittings  | - | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 4 (4 x 1) | 4 (4 x 1) | 4 (4 x 1) |
| Number of outputs/circuits | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 4 Individually addressable | 4 | 4 Individually addressable |
| Dimmable | No | No | No | 0/1-10V | DALI | No | Casambi | 0 / 1-10V (0-100%)* | DALI / DALI-2 | 0 / 1-10V (0-100%)* | DALI | DALI / DMX |
| Output current (mA) | 350mA | 350mA | 350mA | 350mA | 350mA | 350mA | 350mA | 350mA | 350mA | 350mA | 350mA | 350mA |
| Output voltage (V) | 9-29V | 3-40V | 2-41V | 3-43V | 10-49V | 2-55V | 2-55V | 2-55V | 2-55V | 2-57V per channel | 2-57V per channel | 2-57V per channel |
| Max output wattage (W) | 10W | 14W | 15W | 15W | 17W | 30W | 30W | 30W | 30W | 100W | 100W | 100W |
| Dimensions L x W x H (mm) | 67 x 41 x 34 | 79 x 38 x 25 | 115 x 34 x 19 | 111 x 52 x 22 | 111 x 52 x 22 | 210 x 40 x 34 | 210 x 40 x 34 | 210 x 40 x 34 | 210 x 40 x 34 | 388 x 42 x 30 | 388 x 42 x 30 | 388 x 42 x 30 |
| Hole cut-out (mm) | Ø53 | Ø44 | Ø40 | Ø58 | Ø58 | Ø51 | Ø51 | Ø51 | Ø51 | N/A | N/A | N/A |
| IP rated | IP67 | IP67 | Drivers can be supplied with an IP rated box for use in wet environments (sold separately). | | | | | | | | | |
| Warranty | 3 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years |



Wiring in series

LED's should be wired 'in-series'. In a series circuit, all components are connected end-to-end, forming a single path for current to flow.

NB: (number of circuits) x (number of LEDs)

* Dimming range can vary depending on the manufacturer and type of control system used

500mA LED DRIVERS


Constant Current Drivers

LEDs use specific drivers to run them, they are different from normal low voltage fittings in that they must be wired in series and need a constant current. Drivers can be placed 10m from the LEDs. Longer distances of 10-40m can be achieved by using a larger diameter cable to reduce the volt drop, or taking one LED off the maximum that the driver can run. Please contact us for more information.

Example fittings that use these drivers include: LD42-500, LD36-500, LD26-500

Replaces TXDL12CC500

| 500mA Constant Current Drivers |  |  |  |  |  |  |  |  |  |  |  |
|---|---|---|---|--|---|---|---|---|---|---|---|
| | TX.DALV500S | TXDTC500S | TXDTC500D | TXDTC500DALI | TXDEL500S | TXDEL500CAS | TXDEL500D | TXDEL500DALI | TXDEL4S500D | TXDEL4A500DALI-1 | TXDEL4A500DMX TXDEL4A500DALI |
| Brand | Alvit | TCI | TCI | TCI | eldoLED | eldoLED | eldoLED | eldoLED | eldoLED | eldoLED | eldoLED |
| 1.7W fittings  | 1-8 | 1-7 | 1-12 | 2-12 | 1-16 | 1-16 | 1-16 | 1-16 | 60 (4 x 1-15) | 60 (4 x 1-15) | 60 (4 x 1-15) |
| 5.1W (3x1.7W) fittings  | 1-2 | 1-2 | 1-3 | 1-3 | 1-4 | 1-4 | 1-4 | 1-4 | 16 (4 x 1-4) | 16 (4 x 1-4) | 16 (4 x 1-4) |
| 7W fittings  | 1-2 | 1 | 1-3 | 1-3 | 1-4 | 1-4 | 1-4 | 1-4 | 16 (4 x 1-4) | 16 (4 x 1-4) | 16 (4 x 1-4) |
| 5W fittings  | 1-2 | 1-2 | 1-3 | 1-3 | 1-5 | 1-5 | 1-5 | 1-5 | 20 (4 x 1-5) | 20 (4 x 1-5) | 20 (4 x 1-5) |
| 10W fittings  | 1 | 1 | 1-2 | 1-2 | 1-2 | 1-2 | 1-2 | 1-2 | 8 (4 x 1-2) | 8 (4 x 1-2) | 8 (4 x 1-2) |
| 20W fittings  | - | - | 1 | 1 | 1 | 1 | 1 | 1 | 4 (4 x 1) | 4 (4 x 1) | 4 (4 x 1) |
| Number of outputs/circuits | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 4 Individually addressable | 4 | 4 Individually addressable |
| Dimmable | No | No | 0/1 - 10V | DALI | No | Casambi | 0/1 - 10V (0-100%)* | DALI / DALI-2 | 0/1 - 10V (0 - 100%)* | DALI (0 - 100%)* | DALI / DMX |
| Output current (mA) | 500mA | 500mA | 500mA | 500mA | 500mA | 500mA | 500mA | 500mA | 500mA | 500mA | 500mA |
| Output voltage (V) | 3- 28V | 2-24V | 2-40V | 5-40V | 2-55V | 2-55V | 2-55V | 2-55V | 2-57V per channel | 2-57V per channel | 2-57V per channel |
| Max output wattage (W) | 14W | 12W | 20W | 20W | 30W | 30W | 30W | 30W | 100W | 100W | 100W |
| Dimensions L x W x H (mm) | 79 x 38 x 25 | 115 x 34 x 19 | 111 x 52 x 22 | 111 x 52 x 22 | 210 x 40 x 34 | 210 x 40 x 34 | 210 x 40 x 34 | 210 x 40 x 34 | 388 x 42 x 30 | 388 x 42 x 30 | 388 x 42 x 30 |
| Hole cut-out (mm) | Ø44 | Ø40 | Ø58 | Ø58 | Ø51 | Ø51 | Ø51 | Ø51 | N/A | N/A | N/A |
| IP rated | IP67 | Drivers can be supplied with an IP rated box for use in wet environments (sold separately). | | | | | | | | | |
| Warranty | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years |



Wiring in series

LED's should be wired 'in-series'. In a series circuit, all components are connected end-to-end, forming a single path for current to flow.

NB: (number of circuits) x (number of LEDs)

* Dimming range can vary depending on the manufacturer and type of control system used


700mA LED DRIVERS

Constant Current Drivers

LEDs use specific drivers to run them, they are different from normal low voltage fittings in that they must be wired in series and need a constant current. Drivers can be placed 10m from the LEDs. Longer distances of 10-40m can be achieved by using a larger diameter cable to reduce the volt drop, or taking one LED off the maximum that the driver can run. Please contact us for more information.

Example fittings that use these drivers include: LD56-700, LD51-700, LD38-700

| 700mA Constant Current Drivers |  |  |  |  |  |  |  |  |  |  |  |
|--|---|---|---|--|---|---|---|---|---|---|---|
| | TX.DALV700S | TX.DTC700S | TXDTC700D | TXDTC700DALI | TXDEL700S | TXDEL700CAS | TXDEL700D | TXDEL700DALI | TXDEL4S700D | TXDEL4A700DALI-1 | TXDEL4A700DMX TXDEL4A700DALI |
| Brand | Alvit | TCI | TCI | TCI | eldoLED | eldoLED | eldoLED | eldoLED | eldoLED | eldoLED | eldoLED |
| 2.4W fittings  | 1-6 | 1-7 | 1-8 | 1-8 | 1-12 | 1-12 | 1-12 | 1-12 | 40 (4 x 1-10) | 40 (4 x 1-10) | 40 (4 x 1-10) |
| 10W fittings  | 1 | 1 | 1-2 | 1-2 | 1-3 | 1-3 | 1-3 | 1-3 | 8 (4 x 1-2) | 8 (4 x 1-2) | 8 (4 x 1-2) |
| 7W fittings  | 1 | 1-2 | 1-2 | 1-2 | 1-4 | 1-4 | 1-4 | 1-4 | 12 (4 x 1-3) | 12 (4 x 1-3) | 12 (4 x 1-3) |
| 14W fittings  | 1 | 1 | 1 | 1 | 1-2 | 1-2 | 1-2 | 1-2 | 4 (4 x 1) | 4 (4 x 1) | 4 (4 x 1) |
| Number of outputs/circuits | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 1 | 4 | 4 | 4 Individually addressable |
| Dimmable | No | No | 0/1 - 10V | DALI | No | Casambi | 0 - 10V (0 - 100%)* | DALI / DALI - 2 | 0/1 - 10V (0 - 100%)* | DALI | DMX/DALI |
| Output current (mA) | 700mA | 700mA | 700mA | 700mA | 700mA | 700mA | 700mA | 700mA | 700mA | 700mA | 700mA |
| Output voltage (V) | 3-20V | 3-24V | 2-29V | 3-28V | 2-42V | 2-42V | 2-42V | 2-42V | 2-37.5V | 2-37.5V | 2-37.5V |
| Max output wattage (W) | 14W | 17W | 20W | 20W | 30W | 30W | 30W | 30W | 100W | 100W | 100W |
| Dimensions L x W x H (mm) | 79 x 38 x 25 | 125 x 38 x 22 | 111 x 52 x 22 | 111 x 52 x 22 | 210 x 40 x 34 | 210 x 40 x 34 | 210 x 40 x 34 | 210 x 40 x 34 | 388 x 42 x 30 | 388 x 42 x 30 | 388 x 42 x 30 |
| Hole cut-out (mm) | Ø44 | Ø44 | Ø58 | Ø58 | Ø51 | Ø51 | Ø51 | Ø51 | N/A | N/A | N/A |
| IP rated | IP67 | Drivers can be supplied with an IP rated box for use in wet environments (sold separately). | | | | | | | | | |
| Warranty | 5 years | 2 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years |



Wiring in series

LED's should be wired 'in-series'. In a series circuit, all components are connected end-to-end, forming a single path for current to flow.


NB: (number of circuits) x (number of LEDs)


* Dimming range can vary depending on the manufacturer and type of control system used


PHASE / MAINS DIMMABLE LED DRIVERS

Constant Current Drivers

Phase/mains dimmable drivers must always be specified with care as there are many factors that can effect how well they dim. If possible on a project it is best to use mains dimmable drivers from the same manufacturer, especially if they are on the same room or circuit. Drivers can be placed 10m from the LEDs. Longer distances of 10-40m can be achieved by using a larger diameter cable to reduce the volt drop, or taking one LED off the maximum that the driver can run. Please contact us for more information.

| 350mA Constant Current Drivers | |  |
|-----------------------------------|-----------------------|---|
| | | TXDTC350PHD |
| Brand | | TCI |
| 1.2W fittings | ⊙ 1 LED | 1-14 |
| 3.6W (3x1.2W) fittings | ⊙⊙ 3 LED | 1-3 |
| 5W fittings | ⊕ E1 / E2 / E3 Engine | 1-3 |
| 3. 5W fittings | ⊙ F1 Engine | 1-4 |
| 7W fittings | ⊙⊙ 6 LED & N1 Engine | 1-2 |
| 14W fittings | ⊙⊙ P1 Engine | 1 |
| Number of outputs/circuits | | 1 |
| Dimmable | | 240V trailing & leading edge (5 - 100%) |
| Output current (mA) | | 350mA |
| Output voltage (V) | | 2-47V |
| Max output wattage (W) | | 17W |
| Dimensions LxWxH (mm) | | 166 x 46 x 34 |
| Hole cut-out (mm) | | Ø55 |
| IP rated | | Can be supplied with an IP rated box for use in wet environments. (Sold separately) |

| 500mA Constant Current Drivers | |  |
|-----------------------------------|-----------------------|---|
| | | TXDTC500PHD |
| Brand | | TCI |
| 1.7W fittings | 1 LED | 1-14 |
| 5.1W (3x1.7W) fittings | 3 LED | 1-3 |
| 7W fittings | ⊕ E1 / E2 / E3 Engine | 1-3 |
| 5W fittings | ⊙ F1 Engine | 1-4 |
| 10W fittings | ⊙⊙ 6 LED & N1 Engine | 1-2 |
| 20W fittings | ⊙⊙ P1 Engine | 1 |
| Number of outputs/circuits | | 1 |
| Dimmable | | 240V trailing & leading edge (5 - 100%) |
| Output current (mA) | | 500mA |
| Output voltage (V) | | 2-47V |
| Max output wattage (W) | | 24W |
| Dimensions LxWxH (mm) | | 166 x 46 x 34 |
| Hole cut-out (mm) | | Ø55 |
| IP rated | | Can be supplied with an IP rated box for use in wet environments. (Sold separately) |

| 700mA Constant Current Drivers | |  |
|-----------------------------------|-----------------------|---|
| | | TXDTC700PHD |
| Brand | | TCI |
| 2.4W fittings | 1 LED | 1-14 |
| 10W fittings | ⊕ E1 / E2 / E3 Engine | 1-3 |
| 7W fittings | ⊙ F1 Engine | 1-4 |
| 14W fittings | ⊙⊙ 6 LED & N1 Engine | 1-2 |
| Number of outputs/circuits | | 1 |
| Dimmable | | 240V trailing & leading edge (5 - 100%) |
| Output current (mA) | | 700mA |
| Output voltage (V) | | 2-46V |
| Max Output Wattage (W) | | 32W |
| Dimensions LxWxH (mm) | | 166 x 46 x 34 |
| Hole Cut - out (mm) | | Ø55 |
| IP Rated | | Can be supplied with an IP rated box for use in wet environments. (Sold separately) |
| Warranty | | 5 years |



NB: TXDTC350 / 500 / 700PHD drivers are not compatible with Mode leading edge control systems.



DYNAMIC LED DRIVERS



Constant Current Drivers

Dynamic LED drivers allow the control of multiple circuits from one driver. This provides the ability to control colour changing fittings in the form of either RGB, RGBW or Tunable White LEDs. Drivers can be placed 10m from the LEDs. Longer distances of 10-40m can be achieved by using a larger diameter cable to reduce the volt drop, or by taking one LED off the maximum that the driver can run. Please contact us for more information.

Example fittings that use these drivers include: LD151, LD10238, LD175

| 350mA Constant Current Drivers |  |  |
|-----------------------------------|---|---|
| | TXDEL2A350DALI | TXDEL4A350DALI TXDEL4A350DMX |
| Brand | eldoLED | eldoLED |
| Linear tunable | 34 (1-17 x CW, 1x17 x WW) | 68 (2-17 CW, 2 x 17 WW) |
| Linear RGB/W | - | 1-14 |
| Fittings tunable and RGB/W | 1-7 Tunable white only | 1-14 |
| Number of circuits | 2 Individually addressable | 4 Individually addressable |
| Dimmable | DALI / DALI-2 | DALI / DMX |
| Suitable for | Tunable White | RGB, RGBW, Tunable White |
| Output current (mA) | 350mA | 350mA |
| Output voltage (V) | 2-55V per channel | 2-57V Per channel |
| Max output wattage (W) | 50W | 100W |
| Dimensions L x W x H | 153 x 76 x 30 | 388 x 42 x 30 |
| Hole cut-out (mm) | N/A | N/A |
| IP rated | Can be supplied with an IP rated box for use in wet environments (sold separately). | |
| Warranty | 5 years | 5 years |

| 500mA Constant Current Drivers |  |  |
|-----------------------------------|---|---|
| | TXDEL2A500DALI | TXDEL4A500DALI TXDEL4A500DMX |
| Brand | eldoLED | eldoLED |
| Linear tunable | 30 (1-15 x CW, 1x15 x WW) | 60 (2-15 CW, 2 x 15 WW) |
| Linear RGB/W | - | 1-14 |
| Fittings tunable and RGB/W | 1-7 Tunable white only | 1-14 |
| Number of circuits | 2 Individually addressable | 4 Individually addressable |
| Dimmable | DALI / DALI-2 | DALI / DMX |
| Suitable for | Tunable White | RGB, RGBW, Tunable White |
| Output current (mA) | 500mA | 500mA |
| Output voltage (V) | 2-55V per channel | 2-57V Per channel |
| Max output wattage (W) | 50W | 100W |
| Dimensions L x W x H | 153 x 76 x 30 | 388 x 42 x 30 |
| Hole cut-out (mm) | N/A | N/A |
| IP rated | Can be supplied with an IP rated box for use in wet environments (sold separately). | |
| Warranty | 5 years | 5 years |

| 700mA Constant Current Drivers |  |  |
|-----------------------------------|---|---|
| | TXDEL2A700DALI | TXDEL4A700DALI TXDEL4A700DMX |
| Brand | eldoLED | eldoLED |
| Linear tunable | 28 (1-14 x CW, 1-14 x WW) | 40 (2 x 1-10 CW, 2 x 1-10 WW) |
| Linear RGB/W | - | 1-10 |
| Fittings tunable and RGB/W | 1-7 Tunable white only | 1-10 |
| Number of circuits | 2 Individually addressable | 2 Individually addressable |
| Dimmable | DALI / DALI-2 | DALI / DMX |
| Suitable for | Tunable White | RGB, RGBW, Tunable White |
| Output current (mA) | 700mA | 700mA |
| Output voltage (V) | 2-55V per channel | 2-37.5V Per channel |
| Max output wattage (W) | 50W | 100W |
| Dimensions L x W x H | 153 x 76 x 30 | 388 x 42 x 30 |
| Hole cut-out (mm) | N/A | N/A |
| IP rated | Can be supplied with an IP rated box for use in wet environments (sold separately). | |
| Warranty | 5 years | 5 years |

RGB/ RGBW LED note:

Green and blue LEDs have a maximum forward voltage of 3.8V (white is max 3.2V at 350mA). So take off 1 LED of the total the driver can run. TXDEL4A350 DMX/ DALI drivers list the amount of RGB and RGBW LEDs they can run.









NB: (number of circuits) x (number of LEDs)







* Dimming range can vary depending on the manufacturer and type of control system used







350mA - 700mA LED DRIVERS (24V INPUT)

Constant Current Drivers

These drivers require a 24V input and provide an output of either 350mA, 500mA or 700mA constant current supply. This makes them particularly useful for boat applications where there is only a 24V supply. The drivers can be dimmed using a pulse width modulation signal (PWM) from a TXDEL DIM controller (see 24V LED driver section).

| 350mA 24V DC Input |  |  |
|--|---|---|
| | TXDT24V350 | TXDT24V350IP68 |
| Brand | TCl | LightGraphix |
| 1.2W fittings  | 1-6 | 1-6 |
| 3.6W (3x1.2W) fittings  | 1-2 | 1-2 |
| 5W fittings  | 1 | 1 |
| 3.5W fittings  | 1-2 | 1-2 |
| 7W fittings  | 1 | 1 |
| 20W fittings  | | |
| Number of outputs/circuits | 1 | 1 |
| Dimmable | PWM | PWM |
| Output current (mA) | 350mA | 350mA |
| Output voltage (V) | 20V | 20V |
| Dimensions L x W x H (mm) | 58 x 31 x 21 | 57 x 34 x 22 |
| Hole cut-out (mm) | Ø38 | Ø42 |
| IP rating | - | IP68 |
| Warranty | 5 years | 3 years |

| 500mA 24V DC Input |  |  |
|--|---|---|
| | TXDT24V500 | TXDT24V500IP68 |
| Brand | TCl | LightGraphix |
| 1.7W fittings 1 LED | 1-6 | 1-6 |
| 5.1W (3x1.7W) fittings 3 LED | 1-2 | 1-2 |
| 7W fittings  | 1 | 1 |
| 5W fittings  | 1-2 | 1-2 |
| 10W fittings  | 1 | 1 |
| 20W fittings  | | |
| Number of outputs/circuits | 1 | 1 |
| Dimmable | PWM | PWM |
| Output current (mA) | 500mA | 500mA |
| Output voltage (V) | 20V | 20V |
| Dimensions L x W x H (mm) | 58 x 31 x 21 | 57 x 34 x 22 |
| Hole cut-out (mm) | Ø38 | Ø42 |
| IP rating | - | IP68 |
| Warranty | 5 years | 3 years |


| 700mA 24V DC Input |  |  |
|--|---|---|
| | TXDT24V700 | TXDT24V700IP68 |
| Brand | TCl | LightGraphix |
| 2.4W fittings 1 LED | 1-6 | 1-6 |
| 10W fittings  | 1 | 1 |
| 5W fittings  | 1-2 | 1-2 |
| 14W fittings  | 1 | 1 |
| 20W fittings  | | |
| Number of outputs/circuits | 1 | 1 |
| Dimmable | PWM | PWM |
| Output current (mA) | 700mA | 700mA |
| Output voltage (V) | 20V | 20V |
| Dimensions L x W x H (mm) | 58 x 31 x 21 | 57 x 34 x 22 |
| Hole cut-out (mm) | Ø38 | Ø42 |
| IP rating | - | IP68 |
| Warranty | 5 years | 3 years |

* see driver data sheet for more information.

* the information provided above is based on a 24V input.


* see driver data sheet for more information.

* see driver data sheet for more information.



Wiring in series

One driver is used to run multiple LEDs that are wired in series. A 24V power supply feeds one driver. Ideal for use on boats with 24V power supply.











Wiring in parallel


One driver per LED, allowing parallel wiring from 24V power supply








24V LED DRIVERS

Constant Voltage Drivers

LEDs using these drivers require a 24V DC constant voltage input with a parallel wiring method. Max 10m.
Example fittings that use these drivers include: LD Picture Light, LD11, LD Line 15, LD22

| 24V Constant Voltage Drivers |  |  |  |  |  |  |  |  |
|----------------------------------|---|---|---|---|--|---|---|---|
| | TXDA24008 | TXDTC24016DALI | TXDTC24020DIM | TXDTR240318S | TXDTR24035S | TXDTR24060S | TXDTR24100S | TXDTR24200S |
| Brand | TCI | TCI | TCI | Tridonic | Tridonic | Tridonic | Tridonic | Tridonic |
| Output power (W) | 8W | 16W | 20W | 18W | 35W | 60W | 100W | 200W |
| Dimmable | use with Dimming Controller | Integrated Dimming (DALI) controller | Integrated Dimming (1-10) controller | Use with dimming controller | use with Dimming Controller | use with Dimming Controller | use with Dimming Controller | use with Dimming Controller |
| Output voltage (V) | 24V DC | 24V DC | 24V DC | 24V DC | 24V DC | 24V DC | 24V DC | 24V DC |
| Dimensions L x W x H (mm) | 60 x 35 x 22 | 111 x 52 x 22 | 111 x 52 x 22 | 127 x 43x 30 | 142 x 43 x 30 | 225 x 43 x 30 | 295 x 43 x 30 | 325 x 43 x 30 |
| IP rating | Drivers can be supplied with an IP rated box for use in wet environments (sold separately). | | | | | | | |
| Warranty | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years | 5 years |

| 24V Constant Voltage Mains Dimmable Drivers |  |
|---|---|
| | TXDEC24060PHD |
| Brand | Ecopac Power |
| Output power (W) | 60W |
| Dimmable | 240V leading edge dimmable |
| Output voltage (V) | 24V DC |
| Dimensions L x W x H (mm) | 178 x 61 x 24 |
| IP rating | Drivers can be supplied with an IP rated box for use in wet environments (sold separately). |
| Warranty | 3 years |

| 24V Dimming Controllers |  |  |  |  |  |  |  |
|----------------------------------|---|---|--|---|---|---|---|
| | TXDO-DIM | TXDO-DIM DALI | TXDEL-DIM | TXDEL-DIM DALI | TXDEL-DIM DMX | TXDEL-DIM DMX 2CH | TXDEL-DIM RGBW DMX |
| Brand | Osram | Osram | eldoLED | eldoLED | eldoLED | eldoLED | eldoLED |
| Output power (W) | 0 - 120W | 0 - 240W | 192W | 192W | 192W | 192W | 4 x 36W |
| Number of channels | 1 | 4 | 1 | 1 | 1 | 2 | 4 |
| Dimmable | 1 - 10V (0 - 100%) | DALI/DALI-2 (0 - 100%) | 0-10V (0 - 100%) | DALI (0 - 100%) | DMX (0 - 100%) | DMX (0 - 100%) | DMX (0 - 100%) |
| Output voltage (V) | 24V DC | 24V DC | 24V DC | 24V DC | 24V DC | 24V DC | 24V DC |
| Dimensions L x W x H (mm) | 172 x 42 x 20 | 181 x 42 x 20 | 153 x 50 x 23 | 153 x 50 x 23 | 153 x 50 x 23 | 153 x 50 x 23 | 153 x 50 x 23 |
| IP rating | Dimming controllers can be supplied with an IP rated box for use in wet environments (sold separately). | | | | | | |
| Warranty | 3 years | 3 years | 5 years | 5 years | 5 years | 5 years | 5 years |

Please Note: Dimming drivers must be tested with control systems to assess compatibility. Dimming range can vary depending on the manufacturer of the dimmer / control system.